

# VCI-300MKII DJ CONTROLLER



## TOP OF THE LEAGUE

### INTRODUCTION

In 2008, the VCI-300+ITCH was the beginning for Vestax and Serato to create a new DJ console of the next generation. The goal was clear. To design a light weight and compact digital DJ instrument with the touch of analog control.

Preserving the concept of the award winning VCI-300+ITCH, the VCI-300MKII comes with usability improvements based on feedback from VCI-300 customers.

Vestax has considered every comment that has been received, and have put them all in act. Simply to give DJs what they want.

### WHAT'S NEW?

- > Headphones and master volume boost
- > Jog sensor control
- > Direct audio thru
- > Mini headphones jack
- > Optional Vestax digital fader

## CLOSE-UP

### 1. Volume Boost (GAIN BOOST)

Higher output gain level and headphone volume level when supplying power with the optional power adaptor. (not included)

### 2. JOG sensor control

New adjust knobs for speedy and accurate control.

### 3. Direct Audio Thru


Audio fed to the MIC/AUX input can now be directly sent to the Master outputs with the THRU switch turned ON, minimizing latency of when fed through ITCH.

### 4. Optional Vestax Digital Fader (not included)

The VCI-300 Cross fader can be upgraded to Vestax's new magnetic sensor system digital fader CF-X2.

### 5. Mini headphone jack

1/8 inch headphone connection along with standard 1/4 inch connection



## SYSTEM REQUIREMENTS

#### A) Windows XP

OS : XP SP2 or higher  
32&64bit is supported  
CPU : Pentium4 mobile 2GHz or higher  
RAM : 1GB or higher  
Others : 1024x768 screen resolution  
Hard disk space for music  
Available USB port

NOTE : Intel Celeron, ATOM, AMD is not supported.

#### B) Windows Vista&7

OS : Vista SP1 or higher  
32&64bit is supported  
CPU : Intel Core Duo 1.6GHz or higher  
RAM : 1GB or higher  
Others : 1024x768 screen resolution  
Hard disk space for music  
Available USB port

#### C) Macintosh

OS : Mac OS X 10.5 or higher  
CPU : Intel Core Duo 1.6GHz or higher  
RAM : 1GB or higher  
Others : 1024x768 screen resolution  
Hard disk space for music  
Available USB port

## SPECIFICATIONS

USB Port (Bus powered)  
MIC INPUT x 1  
AUX INPUT : RCA x 2  
HEADPHONES OUT x 2 (3.5mm & 6.3mm)  
MASTER OUT : PHONE x 2, RCA x 2

INPUT FADER CURVE CONTROL x 1  
CROSS FADER CURVE CONTROL x 1  
DIMENSIONS : 410(W)x43(H)x275(D)  
(Excluding knob height)  
WEIGHT : 3.2kg  
# ADAPTOR (OPTION) : DC-7.5V 500mA

Bundled items:  
ITCH software (CD-ROM)  
USB cable

Replacement fader (not included)  
IF-300 / CF-300